### Daniels delivers laundry's latest evolution - the innovation of LG.

The commercial laundry series from LG offers state-of-the-art technologies with superior reliability and the greatest energy efficiencies. Common area laundry rooms equipped with LG equipment are the performance-driven solution delivering the better wash results, sustainability and dependability.

### • Industry-leading energy efficiencies

LG streamlines energy usage through its front load design and innovative direct-drive motor effectively reducing consumption and decreasing your carbon footprint. The card and coin washers advanced performance and largest load capacity in the industry were designed to consume less water and energy per pound of laundry than any other commercial frontload brand.

### • Greater reliability and superior design

The LG brand evokes expertise and excellence in appliances. The new, enhanced laundry systems are no exception and have been designed to meet this high standard. LG appliances are more dependable, quieter and have a longer life – guaranteeing better operations.



Laundry's latest evolution, exclusively from Daniels Equipment Co., Inc.

> 1-800-258-3570 www.Danielsequipment.com Email: sales@decequip.com



## Card Type Washer GCW1069CS





# LG High-Efficiency Front Load Washer

#### **Washer Specifications**

Color	White
Electrical	120 Volt, 5 Amp
MEF	2.60
WF (Water per Cubic Foot)	3.65
ENERGY STAR®	Yes
Dimensions (WxDxH)	27"(W) x 30-1/4"(D) x 38-11/16"(H) (50-13/16"D with door open) Height to top of meter case (Coin) 48"
Weight	191 lbs.
Washing Capacity	4.2 cu. ft. (IEC) 3.63 cu. ft. (DOE)
Washing RPM	1150 RPM
Extract G-Force (RPM) s/b	413 (1150)
Water Consumption	11.2 gal / 42.4 L (minimum)
Water Level	10 step (by sensor)
Wash Cycles	4
Operation Time (normal)	29 min (minimum)
Body Material	Painted steel
Top Plate Material	Porcelain
Additional Programming Functions	Washing Time Control Function Rinsing Time Control Spinning Time Control Change Vend Price Control Special Day Price Control Extra Washing Selection Auto Restart